

PCT/IL 99/00479

09/926547



STATE OF ISRAEL

REC'D 07 OCT 1999

WIPO PCT

This is to certify that  
annexed hereto is a true  
copy of the documents as  
originally deposited with  
the patent application  
particulars of which are  
specified on the first page  
of the annex.

זאת לתעודה כי  
רצופים בזה העתקים  
נכונים של המסמכים  
שהופקדו לכתחילה  
עם הבקשה לפטנט  
לפי הפרטים הרשומים  
בעמוד הראשון של  
הנספח.

## PRIORITY DOCUMENT

SUBMITTED OR TRANSMITTED IN  
COMPLIANCE WITH RULE 17.1(a) OR (b)

07-09-1999

This \_\_\_\_\_ היום

ממנה  
המנהל

רשם הפטנטים  
Registrar of Patents

נתאשר

לשימוש הלשכה  
For Office Use

חוק הפטנטים, תשנ"ז  
PATENTS LAW, 5727-1967

בקשה לפטנט

Application for Patent

141/00863

130038	Number
19-05-1999	תאריך: Date
	הוקדם/נדחה Ante/Post-dated

אני, (שם המבקש, מענו - ולגבי גוף מאוגר - מקום התאגדותו)  
I (Name and address of applicant, and, in case of body corporate-place of incorporation)

Lenslet Ltd.  
6 Wissotzky St.  
Tel Aviv 62338

לנסלט בע"מ  
רח' ויסוצקי 6  
תל אביב 62338

בעל אמצאה מכה  
Owner, by virtue of  
העברה  
Assignment  
שמה הוא  
of an invention, the title of which is

Image Compression

דחיסת תמונה  
(בעברית)  
(Hebrew)

(באנגלית)  
(English)

hereby apply for a patent to be granted to me in respect thereof.

מבקש בזאת כי ינתן לי עליה פטנט

* בקשת חלוקה - Application of Division		* בקשת פטנט מוסף - Application for Patent Addition		* דרישה דין קדימה Priority Claim		
מבקשת פטנט from Application	* לבקשה/לפטנט to Patent/Appl.	מספר/סימן Number/Mark	תאריך Date	מדינת האגוד Convention Country		
No. _____ dated _____ מיום	No. _____ dated _____ מיום					
* יפוי כח: כללי/מיוחד - רצוף בזה / <u>עוד יוגש</u> P.O.A.: general / individual - attached / to be filed later - הוגש בענין _____ המקום למסירת הודעות ומסמכים בישראל Address for Service in Israel <u>מנסטר ושתי</u> <u>עורכי פטנטים בע"מ</u> <u>רח' בזל 16 פינת</u> <u>ת.ד. 10256 פינת, 49002</u>						
חתימת המבקש Signature of Applicant <u>אגור האבק</u> <u>מנסטר ושתי</u> <u>עורכי פטנטים בע"מ</u>		1999 מאי 19 שנת _____ of the year בחודש _____ of היום This				
		לשימוש הלשכה For Office Use				

141/00863

דחיסת תמונה

Image Compression

Lenslet Ltd.  
c:141/00863

לנסלט בע"מ

IMAGE COMPRESSION  
FIELD OF THE INVENTION

The present invention relates to the field of optical processing and especially to compressing images using optical components.

BACKGROUND OF THE INVENTION

Often, the information bandwidth to be transmitted is greater than the available bandwidth. Therefore, information is often compressed before it is transmitted (or stored), to reduce the required bandwidth. For example, the HDTV standard was defined, at its inception, to include compression. Many types of signals are compressed, including still images, video and telephone conversations. The reigning compression standards are JPEG for still images and MPEG (I, II, III or IV) for video. In actuality, these standards are standards for the compressed signals. There is no particular requirements, in the standard, on the method for converting the uncompressed signals into compressed signals.

Compression and in some cases decompression are often very demanding and typically require dedicated hardware. Both JPEG and MPEG are transform-based methods, in which the uncompressed data is transformed into a transform space, where the data is represented by a set of coefficients. It is usually desirable that the coefficients have less autocorrelation than the image data or even no autocorrelation at all. Although the DCT transform does not completely decorrelate the coefficients, the correlation between them is significantly reduced. In other compression methods, other transform spaces are used. In transform space, some of the coefficients have a greater visual and/or other effect on the image, than other coefficients. To obtain compression, the coefficients are quantized, with fewer bits being allocated to those coefficients which have a lesser effect. Typically, a coefficient is quantized by dividing it by a weight and then rounding or truncating the result.

Optical and electro-optical processors have been used in the art, to a small extent, for computationally demanding applications. However, with the advent of very fast electronic computer components and parallel processors, their acceptance has been limited.

Performing some types of linear transforms, for example Fourier transforms, continuous cosine transforms and Walsh transforms, using optical components is well known, for example, as described in "Cosinusoidal Transforms in White Light", by N. George and S. Wang, in Applied Optics, Vol. 23, No. 6, March 15, 1984, in "Hartley Transforms for Hybrid Pattern Matching", by Nomura, K. Itoh and Y. Ichioka, in Applied Optics, Vol. 29, No. 29, October, 10, 1990, in "Lens Design for a White-Light Cosine-Transform Achromat", by K. B. Farr and S. Wang, in Applied Optics, Vol. 34, No. 1, January 1, 1995 and in "Optical

Computing", by D. Feitelson, in a chapter titled "Optical Image and Signal Processing", pp. 102-104 (which pages describe general discrete linear transforms using a lenslet array), and pp. 117-129 (which describe matrix multiplication), MIT Press 1988, the disclosures of which are incorporated herein by reference.

## SUMMARY OF THE INVENTION

5 An object of some preferred embodiments of the invention is efficient and/or fast generation of compressed still and moving images, especially transform based compression methods. In a preferred embodiment of the invention, this object is achieved by using optical components which perform specific steps of a compression method. Some compression  
10 methods utilize models, e.g., of visual perception to provide lossy compression. In a preferred embodiment of the invention, the optical components used are selected to match physical processes and/or models which are mimicked by the compression method. Alternatively or additionally, the optical components are selected to perform computation-intensive steps, for example transforms, which can be performed effectively using optical components.

15 A compression system in accordance with a preferred embodiment of the invention preferably comprises five stages, an input which receives the data to be compressed, an optional pre-processing stage which converts the representation of the data into a presentation more suitable for processing, a processing stage which performs the compression, an optional post processing stage which converts the representation of the compressed data into one  
20 suitable for output and an output stage which outputs the data. In a preferred embodiment of the invention, some or all of the stages are optical. In some embodiments, one or more electronic or hybrid electronic and optical stages may be used, for example for pre-processing the data. Additionally, in some embodiments, only some of the processing is performed optically, with the balance of the processing preferably being performed electronically.

25 An aspect of some preferred embodiments of the invention relates to optical block transforms, especially of image data. In a preferred embodiment of the invention, an optical component is used to transform image data in blocks, with each block being transformed separately. In a preferred embodiment of the invention, the transform used is a DCT (Discrete Cosine Transform) transform, preferably a JPEG-DCT, which is the DCT transform variant  
30 used for JPEG. Alternatively or additionally, the transform is a wavelet transform, such as the S transform, S+P transform family, other integer to integer "wavelet-like" transforms, or general known wavelet transform (Daubechies etc.) useful for wavelet compression.

Preferably, the block size is 8x8, which is a standard block size for many applications. Alternatively, different block sizes may be used, for example 16x16 or 64x64, possibly with

different block sizes and/or block aspect ratios for different parts of the image. For wavelet transforms, larger blocks are preferably used.

An aspect of some preferred embodiments of the invention relates to performing a DCT (Discrete Cosine Transform) using optical processing, preferably a JPEG-DCT. In a preferred embodiment of the invention, a single optical element is used to transform data from an image domain to a DCT domain. A related aspect is an optical element which performs discrete wavelet and "integer to integer" wavelet transforms (such as the S and S+P transforms), for example using a combination of diffraction gratings neutral density filters (for weighting sums and differences).

An aspect of some preferred embodiments of the invention relates to a block-DCT-transforming lens, preferably a JPEG-DCT performing lens. In a preferred embodiment of the invention, such a lens comprises a two dimensional matrix of groups of optical elements, each such group performing a DCT on a single block. Preferably, such a group comprises a lenslet array which performs the DCT directly. Alternatively, the matrix comprises a matrix of optical elements, with each optical element performing a DCT transform for a single block. Alternatively to performing a DCT transform, a correspondence between JPEG DCT and DFT (Discrete Fourier Transform) may be utilized, so that a Fourier-transforming lens (or optical element or lenslet array) is used. Preferably, optical or electrical components are provided to modify the data and/or the transformed data so that the Fourier lens generate a DCT transform, at least for real image data. Alternatively to block-DCT lens, a lens for performing other types of block transforms, such as a block-Wavelet-transform, can be provided.

An aspect of some preferred embodiments of the invention relates to performing optical motion estimation. In a preferred embodiment of the invention, the motion estimation is performed on block-DCT-transformed data, by comparing DCT coefficients of neighboring blocks. Preferably the same hardware is used to perform DCT for motion estimation and for image compression. Alternatively or additionally to motion estimation, motion compensation may also be performed by correcting DCT coefficients of transformed data.

An aspect of some preferred embodiments of the invention relates to data compression using optical components. In various preferred embodiments of the invention, individual steps of image compression methods are performed using optical components. In some preferred embodiments of the invention, multiple sequential steps are implemented using optical components, possibly without conversion back to electrical signals in-between steps.

In a preferred embodiment of the invention, the data compressed is image data. Preferably, compression method is a transform based method, especially a DCT based method,

such as JPEG or MPEG. Alternatively or additionally, other type of data compression which require processing (not spatial zooming) may be used, for example, entropy encoding. In a preferred embodiment of the invention, at least the DCT and/or motion estimation steps used for the above compression methods are performed optically. Alternatively, the compression method is a wavelet based compression method.

Alternatively or additionally to compression, data decompression may be effected using optical processing, for example to perform an inverse DCT.

An aspect of some preferred embodiments of the invention relates to direct acquisition of images which are compressed, partially compressed or pre-processed for rapid compression. In a preferred embodiment of the invention, a camera uses a DCT-transforming lens, which receives light from an imaged object and projects a transform of the light onto an optical detector, such as a CCD, for data acquisition. Alternatively, other types of optical detectors, such as a CMOS detector may be used. Preferably, but not necessarily, other optical elements are provided between the DCT lens and the CCD to perform further optical processing and/or image compression on the data. Alternatively or additionally, optical and/or electro-optical elements are provided between the object and the DCT lens to perform pre-processing on the optical data, for example to change its data representation scheme, or to better process polychromatic light. In a preferred embodiment of the invention, the DCT lens accepts polychromatic light. Alternatively, color information is separated out of the light received from the imaged object and the DCT lens accepts monochromatic light. In a preferred embodiment of the invention, the optical processing is used to perform or aid in performing JPEG or MPEG compression. Alternatively or additionally, other compression protocols are performed. Alternatively to DCT lens, other block-transform lens may be provided, for example for an S-transform.

An aspect of some preferred embodiments of the invention relates to using a continuous Fourier-transform optical system, for example a Fourier lens, for performing a discrete transform. In a preferred embodiment of the invention, data to the Fourier lens is matched to a data receptor at the other side of the Fourier lens to allow a discrete transform to be performed.

An aspect of some preferred embodiments of the invention relates to determining a matching between an SLM and a CCD to allow the use of Fourier optics for performing transforms, such as linear transforms. In a preferred embodiment of the invention, the size of elements in the CCD and the SLM is matched. Alternatively or additionally, one or more continuous spatially varying neutral density filter is used to match the CCD to the SLM.

There is thus provided in accordance with a preferred embodiments of the invention, a method of image compression, comprising:

providing image-data encoding light;

transforming said light from an image space to a transform space utilizing an optical component; and

converting said transformed light into electrical signals, which electrical signals represent a compressed representation of said image data. Preferably, said converting comprises converting after quantization.

There is also provided in accordance with a preferred embodiment of the invention, a method of image de-compression, comprising:

providing compressed-image-data encoding light;

transforming said light from a transform space to an image space utilizing an optical component; and

converting said transformed light into electrical signals, which electrical signals represent said image data.

In a preferred embodiment of the invention, said transforming comprises transforming using one or more optical elements which perform a block transform. Preferably, said one or more optical elements comprises a matrix of optical lens elements. Preferably, at least one of said optical lens elements comprises a lenslet array which performs a block transform for a single block.

In a preferred embodiment of the invention, said one or more optical elements comprises an element which performs a vector by matrix multiplication. Alternatively, said one or more optical elements comprises an element which generates a matrix product. Preferably, said matrix product comprises a triple matrix product.

In a preferred embodiment of the invention, said transforming utilizes at least one electrical component for transferring data between said at least one optical component.

In a preferred embodiment of the invention, said image is compressed using a JPEG standard. Alternatively, said image is compressed using an MPEG standard. Alternatively, said image is compressed using a wavelet compression method.

In a preferred embodiment of the invention, said image data represents an image sequence.

There is also provided in accordance with a preferred embodiment of the invention, apparatus for direct acquisition of compressed image data, comprising:

at least one optical element which receives light waves from an imaged object and



which transforms said image into a transform space; and

an optical detector which receives said transformed light and generates electronic signals responsive to said received light. Preferably, the apparatus comprises an optical quantizer which quantizes said transformed light prior to its reception by said detector. Alternatively, the apparatus comprises an electronic quantizer which quantizes said electronic signals to produce compressed data. Alternatively, said optical detector quantizes said light.

Alternatively or additionally, said at least one optical element comprises a single optical element which performs said transforming. Alternatively or additionally, the apparatus comprises a storage unit for storing at least one set of said electronic signals, corresponding to a still image. Alternatively or additionally, the apparatus comprises a storage unit for storing at least one set of said electronic signals, corresponding to an image sequence.

In a preferred embodiment of the invention, said transform space comprises a DCT transform space. Alternatively, said transform space comprises a wavelet transform space.

There is also provided in accordance with a preferred embodiment of the invention, a block-transform optical element, comprising:

a plurality of optical groups each group comprising at least one optical sub-element, wherein each of said optical groups transforms a block of data. Preferably, said at least one sub-element comprises a lenslet array portion. Alternatively or additionally, said plurality of optical groups are arranged as a matrix. Alternatively or additionally, said element performs a JPEG-DCT transform. Alternatively or additionally, said element performs an inverse DCT transform. Alternatively or additionally, said element performs a wavelet transform. Alternatively or additionally, said optical element performs said transform on data arranged as a spatially impulse image.

In a preferred embodiment of the invention, said optical element performs said transform on data arranged as a continuous image. Alternatively or additionally, said transform comprises a linear transform. Alternatively or additionally, said transform comprises a non-separable transform. Alternatively or additionally, said optical groups overlap. Alternatively or additionally, said optical groups do not overlap.

There is also provided in accordance with a preferred embodiment of the invention, a method of DCT-like transforming of data, comprising:

providing optical waves which encode said data; and

passing said waves through at least one optical element, which optical element modifies said optical waves into second optical waves carrying a transform of said data. Preferably, said transform comprises a block transform. Alternatively or additionally, said at

least one optical element is an atomic optical element. Alternatively or additionally, said at least one optical element comprises a plurality of optical elements. Alternatively or additionally, said at least one optical element comprises a discrete optical processing element. Alternatively, said at least one optical element comprises substantially only continuous optical processing element.

In a preferred embodiment of the invention, said transform is a JPEG-DCT transform. Alternatively, said transform is an inverse DCT transform.

There is also provided in accordance with a preferred embodiment of the invention, a method of optical motion estimation, comprising:

providing a first set of light waves encoding data of a first image block;  
DCT transforming said first set of light waves using an optical component;  
providing a second set of light waves encoding data of a second image block;  
DCT transforming said second set of light waves using an optical component; and  
processing said first and said second DCT transformed data sets to determine an amount of relative motion of said two blocks. Preferably, both of said DCT transforms utilize a same optical component for said transforming. Alternatively or additionally, said processing comprises electronically processing said transformed data sets. Alternatively or additionally, the method comprises utilizing said determined motion for generating a compressed image stream.

There is also provided in accordance with a preferred embodiment of the invention, a method of transforming data using a discrete transform, comprising:

preprocessing said data to yield optically encoded data;  
Fourier transforming said data using a Fourier lens; and  
postprocessing said data to yield transformed data. Preferably, said preprocessing comprises optically preprocessing. Preferably, said preprocessing comprises matching said data to said postprocessing. Preferably, said postprocessing comprises acquiring said data and wherein said matching comprises matching to said acquisition. Preferably, said postprocessing comprises spatially modulating said light.

In a preferred embodiment of the invention, said preprocessing comprises spatially modulating said light.

In a preferred embodiment of the invention, said spatially modulating comprises masking said data using an array of pinholes. Alternatively, said spatially modulating comprises continuously varying said amplitude of said data.

In a preferred embodiment of the invention, said preprocessing comprises mirroring

said data. Alternatively or additionally, said transform comprises a JPEG-DCT transform. Alternatively or additionally, said transform comprises a wavelet transform. Alternatively or additionally, said transform comprises an inverse DCT transform.

5 There is also provided in accordance with a preferred embodiment of the invention, apparatus for compressed image data manipulation, comprising:

an input for receiving data;

at least one optical component for transforming said data between an image space and a transform space; and

10 an output for outputting said manipulated data. Preferably, said received data comprises uncompressed image data and comprising a processor for processing said data after said transform to yield compressed image data to be outputted. Preferably, said received data comprises compressed image data and comprising a processor for processing said data before said transform to yield transform data to be transformed by said optical component for said output. Preferably, said processor includes an optical D/A converter. Alternatively, said  
15 processor comprises an optical multiplier for de-quantizing data.

In a preferred embodiment of the invention, said processor performs at least some of its processing on optic waves.

In a preferred embodiment of the invention, said processor performs at least some of its processing on electronic signals. Alternatively or additionally, the apparatus comprises an  
20 optical motion estimator. Preferably, said optical motion estimator utilizes said optical component for optical motion estimation. Alternatively or additionally, said optical motion estimator includes at least one electronic component.

In a preferred embodiment of the invention, the apparatus comprises an optical motion compensator. Preferably, said optical motion compensator utilizes said optical component for  
25 optical motion compensation. Alternatively or additionally, said optical motion compensator includes at least one electronic component. Alternatively or additionally, said data is compressed using a JPEG compression. Alternatively, said data is compressed using a wavelet compression.

In a preferred embodiment of the invention, said data is compressed using an MPEG  
30 compression. Alternatively or additionally, said data comprises an image sequence.

In a preferred embodiment of the invention, said data comprises is a single image. Alternatively or additionally, said data is manipulated as blocks. Preferably, at least two of said blocks are manipulated in parallel. Alternatively, at least two of said blocks are manipulated in series and comprising a buffer circuit for directing said blocks in series into a

single optical component.

In a preferred embodiment of the invention, said optical component comprises a discrete data transforming optical element. Alternatively or additionally, said optical component comprises a holographic lens. Alternatively or additionally, said optical component comprises an acousto-optic element. Alternatively or additionally, said optical component comprises an optical analog to digital converter. Alternatively or additionally, said optical component comprises an optical digital to analog converter. Alternatively or additionally, said optical component comprises matrix product calculating element.

### BRIEF DESCRIPTION OF THE DRAWINGS

The present invention will be more clearly understood from the following detailed description of the preferred embodiments of the invention and from the attached drawings, in which:

Fig. 1 is a flowchart of a baseline method of JPEG-compliant compression;

Fig. 2 is a schematic block diagram of an optical JPEG compression system, in accordance with a preferred embodiment of the invention;

Fig. 3A is a schematic block diagram of a matrix-multiplication based optical DCT component, in accordance with a preferred embodiment of the invention;

Fig. 3B is a schematic block diagram of an optical matrix by vector multiplication component, in accordance with a preferred embodiment of the invention;

Fig. 4A is a schematic diagram of a lens-matrix based 2D DCT component, in accordance with a preferred embodiment of the invention;

Fig. 4B is a schematic diagram of an optical element for the lens matrix of Fig. 4A;

Fig. 4C is a schematic diagram of a lenslet array for the lens matrix of Fig. 4A;

Fig. 4D is a schematic illustration of an optical system for performing a DCT transform using a Fourier lens;

Fig. 5 is a schematic block diagram of an optical JPEG compression system, in accordance with another preferred embodiment of the invention;

Fig. 6 is a schematic flowchart of a base-line method of MPEG-compliant compression;

Fig. 7A is a schematic diagram of a direct-compression camera system, in accordance with a preferred embodiment of the invention;

Fig. 7B is a schematic block diagram of a YUV-separated implementation of the embodiment of Fig. 7A; and

Fig. 8 is a schematic diagram of a lithographic implementation of an optical

compression system in accordance with a preferred embodiment of the invention.

### DETAILED DESCRIPTION OF PREFERRED EMBODIMENTS

Fig. 1 is a flowchart of a base-line method 20 of JPEG-compliant compression. Image data is first transformed using the DCT (Discrete Cosine Transform) (22), to generate a set of coefficients. These coefficients are then quantized (24). The quantized coefficients are then unfolded from a 8x8 representation to a 64x1 representation ("Zig-Zag", 26). These quantized coefficients are encoded using a variable-length encoding scheme (28), zero-run length encoded and then Huffman encoded (30), to reduce entropy. A compressed data file is then generated by prefixing the encoded data with header information (32). Other, similar, methods of JPEG compression are also known.

In accordance with a preferred embodiment of the invention, various of the above steps are performed using optical elements, rather than using electronic or software elements. In the above described JPEG compression method, the step that is typically most computationally demanding, is the DCT step. Thus, in a preferred embodiment of the invention, the DCT step is performed optically.

Fig. 2 is a schematic block diagram of an optical JPEG compression system 50, in accordance with a preferred embodiment of the invention. An electronic input 52 is preferably used to receive the data to be compressed. This element will generally depend on the application for which system 50 is used. For example, if system 50 is implemented on a PC card, electronic input 52 will generally comprises a PC-compatible bus connector. The acquired data is then converted into light, using a spatial light source 54. In a preferred embodiment of the invention, light source 54 comprises an SLM (Spatial Light Modulator) which modulates a beam of light that is reflected from it or that is transmitted through it. Alternatively, source 54 may comprise an array of LEDs, laser diodes, VCELs (vertical cavity emission lasers) or other types of pixelated display devices such as CRT, field effect emitter arrays and plasma displays.

The type of light emitted by source 54 is preferably selected to match an optical DCT unit 56. In some preferred embodiments of the invention, the light from source 54 is coherent (so a laser source is preferably used). In other embodiments, the optics do not require coherent light. In a preferred embodiment of the invention, the light is preferably monochromatic. Alternatively, polychromatic light may be used. In some particular preferred embodiments of the invention, multiple frequencies of monochromatic light are used, for example wherein the frequencies are used to encode attributes of the data, such as its numerical sign. In a preferred embodiment of the invention, the data is encoded using an analog encoding scheme, for

example phase or amplitude. Alternatively, a digital encoding scheme is used. Possibly, as described below, the light may be A/D converted from analog-encoding light into digital-encoding light, for example after it is transformed.

Optical DCT unit 56 transforms the light from an image space to a transform space. Preferably, the transformed light is projected unto a spatial optical sensor 58, such as a CCD array. Details of various types of DCT unit 56 and methods of construction thereof are provided below.

Data is read out of CCD array 58 and then it is quantized, using a quantizer 60. In a preferred embodiment of the invention, the quantization may be performed by setting gain and/or offset characteristic of the CCD and/or individual elements thereof and/or controlling the readout of the CCD, for example to provide a reduced bit-per-pixel ratio. Alternatively, the data is quantized as it is read off the CCD or after it is read off the CCD. Alternatively or additionally, the data is quantized by optical means, such as a second SLM in front of the CCD. The unfolding of the data may be performed before the quantizing or after the quantizing. Then, the data is encoded using a variable length encoding unit 62, Huffman-encoded using a Huffman encoding unit 64 and, finally, a header is attached to the compressed data so that it meets the JPEG standard. Alternatively or additionally, the data is encoded using arithmetic coding (preferably performed by an arithmetic coding unit - not shown).

As will be described below, additional elements of the compression system may be replaced with optical units. In some embodiments of the invention, the different optical units will be interconnected with electrical circuitry, for example for control, data management or data conversion. Thus, even if two consecutive units are embodied using optical means, they may have an intervening step of optical/electrical conversion and then electrical/optical conversion. In other embodiments, the processed light will feed directly from one optical unit to the next. In a preferred embodiment of the invention, a system includes both optical and electronic components and the processing is divided between the components so they can act in parallel. In one example, some of the transforming may be performed optically and some electronically. Such dividing up of work, can better utilize all the elements in a compression/decompression device, especially if some of the components are dual use, for example DSP components.

Optical DCT unit 56 may be implemented in various ways. It should be noted that when compressing images, the DCT transform applied is in actuality a block-DCT transform, where each part of the image is separately transformed.

Fig. 3A is a schematic block diagram of a matrix-multiplication based optical DCT

component 70, in accordance with a preferred embodiment of the invention. The DCT transform can be presented in matrix form as  $[DCT]=[C][T][C]$ . Matrix by matrix multiplication may be performed in many ways, including using multiple repetitions of vector by matrix multiplication, for example as described in "Introduction to Fourier Optics", Goodman, pp. 286, or using direct matrix by matrix multiplication, for example as described in Feitelson, pp. 126-127 (double or triple products), preferably using monochromatic coherent light, or as described in Feitelson, pp. 118, using lenslet arrays, which can accommodate white light; the disclosure of all of which is incorporated herein by reference,

In a vector by matrix embodiment of component 70, a line data provider 72 provides individual lines or columns of an  $8 \times 8$  block to a matrix multiplier 74. The DCT transform of a vector can be performed by multiplying a source vector  $V$  by a convolution matrix  $C$ , to obtain a transformed vector  $T$ . For each  $8 \times 8$  block the lines (or the columns) are individually transformed and then the result is transformed along the individual columns (or lines). In a preferred embodiment of the invention, the data is row transformed using a first unit 74 and is then column transformed using a second multiplication unit 74'. Alternatively, a same unit is used for both the row and column transforms. Preferably, the transformed row data is accumulated using a store unit 76. If each one of the rows is transformed in sequence, the transformed row data may be accumulated using store 76 even if a separate unit 74' is used for column transforms.

Fig. 3B is a schematic block diagram of an optical matrix-by-vector multiplication component 80, in accordance with a preferred embodiment of the invention. When performing a DCT transform, negative-valued results may be produced. Multiplication component 80 separately processes negative- and positive- valued results, to avoid miss-processing. Mathematically, the multiplication of a matrix  $C$  by a vector  $V$  is a linear operation, so that it can be separated in to negative and positive components, e.g.:  $C*V=C_p*V_p+C_n*V_n-C_p*V_n-C_n*V_p$ , where the "n" subscript indicates negative numbers and the "p" subscript indicates positive numbers. In the component of Fig. 3B, vector  $V$  is separated into positive and negative values, which are each separately multiplied by positive or negative valued component matrixes 82 and then summed using subtractors 84 and an adder 86. In a preferred embodiment of the invention, four matrix multiplication units 82 are provided. Alternatively, only two or even only one unit 82 is used, for example to sequentially process negative and positive numbers. In general, the source data is all positive, so that the vector  $V_n$  is empty. It is noted that the DCT of the original image data, which is positive, may be simpler to implement than the DCT of transformed data, which may be negative.

In a preferred embodiment of the invention, sign issues are solved using a bipolar number representation. In a bipolar representation, each number is designated by two components:  $s=[p,n]$ , where  $s$  is a general signed number (not necessarily an integer), and  $[p,n]$  are its positive and negative components.  $s$  is retrieved by setting  $s=p-n$ . Therefore, the number  
 5 -5 can be described by  $[0,5]$ ,  $[3,8]$ ,  $[10,15]$ ,  $[1,6]$  or other combinations of  $p$  and  $n$ , as long as  $p, n > 0$ , and  $p-n=s$ .

The generalized bipolar representation can be adapted to matrix calculation, by representing each number by a 2x2 matrix, of the form

$$\begin{bmatrix} p & n \\ n & p \end{bmatrix}$$

For example:

$$\begin{bmatrix} 1 & -2 \\ 3 & -4 \end{bmatrix} \cdot \begin{bmatrix} 1 & -1 \\ 2 & 2 \end{bmatrix} = \begin{bmatrix} -3 & -5 \\ -5 & -11 \end{bmatrix} \rightarrow \begin{bmatrix} 1 & 0 & 0 & 2 \\ 0 & 1 & 2 & 0 \\ 3 & 0 & 0 & 4 \\ 0 & 3 & 4 & 0 \end{bmatrix} \cdot \begin{bmatrix} 1 & 0 & 0 & 1 \\ 0 & 1 & 1 & 0 \\ 2 & 0 & 2 & 0 \\ 0 & 2 & 0 & 2 \end{bmatrix} = \begin{bmatrix} 1 & 4 & 0 & 5 \\ 4 & 1 & 5 & 0 \\ 3 & 8 & 0 & 11 \\ 8 & 3 & 11 & 0 \end{bmatrix}$$

This representation can be extended to triple product matrix multiplication.

Alternatively to the method of Fig. 3B, negative numbers may be dealt with in other  
 15 ways. In one example, negative and positive numbers are differentiated by their phase. A diffraction grating can be used to divert numbers with one phase value to a different part of a CCD target (or other optical element) than those numbers with a second phase values. In another example, negative numbers are encoded using a different frequency than positive  
 20 numbers. The different frequencies can be separated using suitable gratings or other optical elements. Alternatively or additionally, a self-electro-optical device may use one frequency in order to modulate the other frequency. Alternatively or additionally, a frequency sensitive CCD may be used, for example an RGB CCD. Alternatively or additionally, a CCD may be provided with binary phase or frequency detection, by providing a controllable polarizer or  
 25 spectral filter before the CCD and timing its operation to the acquisition of positive or negative numbers.

Alternatively, negative numbers may be managed by biasing them to be positive, for example, by forcing the results of a DCT to be in the range  $[0...2]$  instead of  $[-1...1]$  (normalized values). In practice, if the maximum DC amplitude is  $A$ , the DCT results are  
 30 shifted by  $+A$ , from the range  $[-A...A]$  to the range  $[0...2A]$ . In the example (described below) where a DCT is performed by mirroring the 8x8 datablock into a 16x16 datablock, a strong spatial delta pulse is provided in the middle of each 16x16 datablock, for example by



controlling the SLM. The effects of this pulse (the bias) are preferably removed using electronic processing after the data is transformed.

Once the data is multiplied, further processing, such as sign extraction or as described below, can be achieved, for example, by performing optical A/D, and then binary operations or by using electronic components.

In the above description, a plurality of matrix-by-matrix or vector-by matrix operations are performed. The number of actually provided multiplication units depends on the implementation and especially on the level of parallelism of the implementation. For example, in one implementation, all the 8x8 blocks are processed in parallel. However, within each block, the multiplications may be performed in parallel (using a plurality of units if required) or in sequence (reusing a single unit for two operations, for example for row and for column DCT). Alternatively or additionally, two or more of the blocks may be processed in series, for example the two blocks sharing a single 8x8 multiplier. Such sequential processing generally requires electronic components, such as store 74, to read and store intermediate results and possibly also for summing up the individual results.

In a preferred embodiment of the invention, each matrix multiplication unit comprises a series of {SLM, lens, CCD} sub-systems which unit accepts electronic data at one end, converts it into optical signals, transforms the data using lens and then converts the transformed data into electronic signals again. Alternatively, a single SLM and/or a single CCD may be shared among several multipliers.

Fig. 4A is a schematic diagram of a lens-matrix based 2D DCT component 90, in accordance with a preferred embodiment of the invention. Light from an image of an object 92 impinges on a lens-matrix 94. Array 94 preferably comprises a plurality of lens-elements 95, each of which performs a DCT on one 8x8 block of image 92. The result of the DCT is recorded by a CCD 96.

Fig. 4B is a schematic diagram of a single optical element 98 suitable for the lens matrix of Fig. 4A, for performing a DCT. Optical element 95 is designed so that light emitted by different portions of the lens corresponds to different coefficients of the DCT transform of the impinging light. Thus, light corresponding to a first DCT coefficient is detected by CCD 96 at a point A. Light corresponding to a second DCT coefficient is detected at a point B. Typically, at least some of the light emitted by lens 95 does not correspond to a DCT coefficient, due to design considerations. Such light may be detected, for instance at a point C. The readout of CCD 96 is preferably configured to account for the correspondence between DCT coefficients and spatial locations on CCD 96. In a preferred embodiment of the

invention, a plurality of or even all of optical elements 98 are combined into a single composite optical element. Alternatively, a single optical element 98 may be implemented as a sequence of individual optical elements.

Fig. 4C is a schematic diagram of a lenslet array 100 for the lens matrix of Fig. 4A, for performing a DCT. In a lenslet array, each individual lenslet preferably generates one DCT coefficient from the impinging light. In one exemplary embodiment, light from a 8x8 block of the image is received by 64 lenslets, preferably arranged in a 8x8 array. After each lenslet is a mask having opaque and transmissive portions and a CCD element is positioned opposite the mask to receive light which passes through the mask. In an exemplary embodiment, each lenslet creates an image of the image to be transformed. Each DCT coefficient  $d(k,l)$  is defined as:

$$d(k,l) = \sum_{i=1}^N \sum_{j=1}^N f(i,j) h(k,l;i,j) \quad (1)$$

where  $f$  is the input and  $h$  is the convolution definition. The opaque and transmissive portions of each of the  $(k,l)$  masks are defined to represent the values of  $h$ , in which the transmissiveness of mask elements for a lenslet  $(k,l)$  are defined to match the relative contribution of those image pixels  $(i,j)$  which take part in determining the  $(k,l)$  coefficient. The CCD element sums the light which passes through the mask, determining the DCT coefficient.

The Formula for a DCT transform and for an inverse DCT transform of an 8x8 block of image data  $f(x,y)$  and an 8x8 block of transform data  $F(u,v)$ , are, respectively:

$$F(u,v) = \frac{1}{4} C(u) C(v) \sum_{x=0}^7 \sum_{y=0}^7 f(x,y) \cos \frac{(2x+1)u\pi}{16} \cos \frac{(2y+1)v\pi}{16}$$

$$f(x,y) = \frac{1}{4} \sum_{u=0}^7 \sum_{v=0}^7 C(u) C(v) F(u,v) \cos \frac{(2x+1)u\pi}{16} \cos \frac{(2y+1)v\pi}{16}$$

where  $C(u)$  and  $C(v)$  are  $1/\sqrt{2}$  for  $u,v=0$  and 1 otherwise.

In a preferred embodiment of the invention, a single large lenslet array is used to implement a matrix of individual lenslet arrays. In a preferred embodiment of the invention, the light from object 92 is focused onto lens matrix 94, so that all of the object is viewed by each one of the lens elements 95. Alternatively, only a block area of the light impinges on each lens element, for example by providing multiple side-by-side lens, each one viewing only a portion of object 92. Alternatively, where an SLM is used, the light which passes through the SLM can be formed of blocks of non-parallel light, so that block portions of the modulated light impinge each on a different lens element 95. Alternatively, especially where individual

optical elements are used, the light from object 92 can be parallel light, so that each optical element receives parallel light from a single block area. In some cases, a lens element may receive light from more than one block area, for example for processing which is beyond the extent of a single block or to provide an overlap between blocks, for example to solve calibration problems.

Fig. 4D is a schematic illustration of an optical system for performing a DCT transform using a Fourier lens. Although in one preferred embodiment of the invention the lens- element directly performs a DCT, in an alternative preferred embodiment of the invention, a correspondence between Fourier transform and DCT is utilized to perform DCT (or other transforms) using a Fourier transform lens. Mathematically, a Fourier transform of real and symmetrical data results in only real (and symmetric) cosine coefficients. The image data to be compressed is typically real. It can be made symmetric by mirroring in the SLM. In order to achieve a discrete transform, the data is preferably provided as an impulse image, with each image portion being a spatial delta function , each of which pulses is transformed using a Fourier transform lens. This type of data provision can be achieved using an SLM with a pinhole filter. In multi-wavelength based embodiments, different pinholes may be designated for different wavelengths. Preferably both the SLM and the CCD are spatially matched according to the following formula:  $\Delta\bar{x} = 0.5\Delta x$  , which defines the distances between the delta

functions (pinholes) in the SLM and  $\Delta u = \frac{\lambda f}{2 \cdot \Delta x \cdot N}$  , which defines the distances between the delta-function receptor in the CCD (can also be modeled by providing a pinhole filter in front of the CCD. In these formula,  $\Delta x$  and  $\Delta u$  are the intervals between delta functions in the SLM and CCD respectively,  $f$  is the focal length,  $N$  is the block size and  $\Delta\bar{x}$  is the placement of the delta function in the interval (phase shift) in the SLM. It can be seen that the pixels intervals in the CCD and the SLM are not-necessarily the same, which may be implemented by ignoring some of the CCD pixels. An alternative matching condition is described below.

In the example of Fig. 4D, an 8x8 block of image 92 is made symmetric using a doubling and mirroring optical system 93 (alternatively to using an SLM) and then transformed by a Fourier lens 97. Since the data is mirrored in two dimensions (only one shown for clarity) a 8x8 block is transformed into a 16x16 block. The result is then combined using a combining optical system 99, to provide an 8x8 DCT transform. In some embodiments of the invention, optical system 93, lens 97 and optical system 99 are combined into a single optical element, thus, the end result is a single optical element which performs a DCT, suitable for use in lens-matrix 94. A matrix of such optical elements may be combined to form a single

optical element which performs a block DCT transform. Alternatively to the optical systems shown, other constructions can be utilized for mirroring, doubling and combining. In one example, an image block is first doubled and arranged as a 2x2 matrix of blocks and then individual blocks of the 2x2 matrix are flipped, to provide the symmetry required for the DCT transform (or other type of transform).

The correspondence between Fourier transform and DCT can also be utilized for other optical transform architectures, for example the matrix-vector multiplication method described above. In another example, a wavelet transform can be performed by mirroring data to be anti-symmetric instead of symmetric, as in the DCT case.

The above matching condition may be derived using the following analysis (for a one dimensional case). The following equation defines the JPEG-DCT which is to be achieved:

$$F(k) = \sum_{n=0}^{N-1=7} f(n) \cdot \cos\left(\frac{\pi k(2n+1)}{2N}\right) \quad (2)$$

Assuming symmetric input, where every block of 16 samples is represented as a combination of delta functions, spaced at intervals of size  $\Delta x$ , and transmitted from a  $\Delta \bar{x}$  position inside each interval:

$$s(x) = \sum_{n=0}^{N-1=7} f(n) \cdot \delta(x - n \cdot \Delta x - \Delta \bar{x}) + \sum_{n=0}^{N-1=7} f(n) \cdot \delta(x + n \cdot \Delta x + \Delta \bar{x}) \quad (3)$$

Applying the optical Fourier transform:

$$\bar{s}(u) = \int_{-\infty}^{\infty} s(x) \cdot e^{-j \frac{2\pi u x}{\lambda f}} dx \quad (4)$$

The imaginary parts cancel out (due to the input being symmetric):

$$\bar{s}(u) = \sum_{n=0}^{N-1=7} f(n) \cdot \cos\left(\frac{2\pi u \cdot (n \cdot \Delta x + \Delta \bar{x})}{\lambda f}\right) \quad (5)$$

Assuming accurate sampling at the Fourier plane (the CCD):

$$\bar{s}(k) = \sum_{n=0}^{N-1=7} f(n) \cdot \cos\left(\frac{2\pi \cdot k \cdot \Delta u \cdot (n \cdot \Delta x + \Delta \bar{x})}{\lambda f}\right) \quad (6)$$

Since equation (2) is desired, we match:

$$\begin{aligned}
\tilde{s}(k) &= \sum_{n=0}^{N-1=7} f(n) \cdot \cos\left(\frac{2\pi \cdot k \cdot \Delta u \cdot (n \cdot \Delta x + \Delta \bar{x})}{\lambda f}\right) = \\
&= \sum_{n=0}^{N-1=7} f(n) \cdot \cos\left(\frac{\pi k (2n+1)}{2N}\right)
\end{aligned} \tag{7}$$

Thus, one matching condition is:

$$5 \quad \cos\left(\frac{2\pi \cdot k \cdot \Delta u \cdot (n \cdot \Delta x + \Delta \bar{x})}{\lambda f}\right) = \cos\left(\frac{\pi k (2n+1)}{2N}\right) \tag{8}$$

Leading to:

$$\frac{\Delta u \cdot \Delta x}{\lambda f} = \frac{1}{2N} \tag{9}$$

and

$$10 \quad \frac{2 \cdot \Delta u \cdot \Delta \bar{x}}{\lambda f} = \frac{1}{2N} \tag{10}$$

resulting in the above matching condition:

$$\begin{cases} \Delta \bar{x} = 0.5 \cdot \Delta x \\ \Delta u = \frac{\lambda f}{2\Delta x \cdot N} \end{cases} \tag{11}$$

15 In some cases, it may be not be suitable to provide delta functions (pinholes or other optical elements) on one or both of the SLM and CCD. The following analysis shows a method of matching a CCD and an SLM, by spatially modulating the light in a less drastic manner, for example using continuous neutral density filters.

The following equation describes an SLM-like object:

$$s(x) = \sum_{n=0}^{N-1=7} f(n) \cdot l(x - n \cdot \Delta x) + \sum_{n=0}^{N-1=7} f(n) \cdot l(x + n \cdot \Delta x) \tag{12}$$

20 Where  $l(x)$  is a general transmission function of the SLM, assumed identical for all pixels, and symmetric, so it can be mirrored. However, it should be noted that a similar but more complex analysis can also be performed in the case where not all the pixels are identical.

After applying the optical (and continuous) Fourier transform:

$$\tilde{s}(u) = \sum_{n=0}^{N-1=7} f(n) \cdot L(u) \cdot \cos\left(\frac{2\pi u \cdot n \cdot \Delta x}{\lambda f}\right) \tag{13}$$

Where  $L(u)$  is the Fourier transform of  $l(x)$ . Since the actual sampling is done by summing all intensities on a detector cell (i.e., a CCD pixel cell), equation (5) transforms to:

$$\tilde{S}(k) = \frac{1}{\Delta u} \int_{k \cdot \Delta u - \Delta \bar{u}/2}^{k \cdot \Delta u + \Delta \bar{u}/2} \tilde{S}(u) \cdot W(u) \cdot du \quad (14)$$

Where  $W(u)$  is the CCD detection weight function. Again, it is assumed that  $W$  is the same for all pixels but this assumption is not required. Using equation (13):

$$\tilde{S}(k) = \frac{1}{\Delta u} \int_{k \cdot \Delta u - \Delta \bar{u}/2}^{k \cdot \Delta u + \Delta \bar{u}/2} W(u) \cdot \left\{ \sum_{n=0}^{N-1} f(n) \cdot L(u) \cdot \cos\left(\frac{2\pi \cdot n \cdot \Delta x}{\lambda f}\right) \right\} \cdot du \quad (15)$$

Since equation (2) is desired, we match:

$$\cos\left(\frac{\pi k(2n+1)}{2N}\right) = \frac{1}{\Delta u} \int_{k \cdot \Delta u - \Delta \bar{u}/2}^{k \cdot \Delta u + \Delta \bar{u}/2} W(u) \cdot L(u) \cdot \cos\left(\frac{2\pi \cdot n \cdot \Delta x}{\lambda f}\right) \cdot du \quad (16)$$

We define:

$$R(u) \equiv W(u) \cdot L(u) / \Delta u \quad (17)$$

The matching requirement is thus:

$$\cos\left(\frac{\pi k(2n+1)}{2N}\right) = \int_{k \cdot \Delta u - \Delta \bar{u}/2}^{k \cdot \Delta u + \Delta \bar{u}/2} R(u) \cdot \cos\left(\frac{2\pi \cdot n \cdot \Delta x}{\lambda f}\right) \cdot du, \quad n, k = 0, 1, \dots, N-1 \quad (18)$$

Which results in the following  $N \times N$  Fredholm I equations (for the 1D case. In 2D its  $N \times N \times N \times N$  equations):

$$\left\{ \begin{array}{l}
 k = 0, n = 0: \\
 \quad \Delta \bar{u}/2 \\
 1 = \int_{\Delta \bar{u}/2} R(u) du \\
 \quad \Delta \bar{u}/2 \\
 k = 0, n = 1: \\
 \quad \Delta \bar{u}/2 \\
 1 = \int_{\Delta \bar{u}/2} R(u) \cos\left(\frac{2\pi \cdot \Delta x \cdot u}{\lambda f}\right) du \\
 \quad \Delta \bar{u}/2 \\
 \dots \\
 k = 1, n = 0: \\
 \quad \Delta u + \Delta \bar{u}/2 \\
 \cos\left(\frac{\pi}{2N}\right) = \int_{\Delta u - \Delta \bar{u}/2} R(u) du \\
 \quad \Delta u - \Delta \bar{u}/2 \\
 k = 1, n = 1: \\
 \quad \Delta u + \Delta \bar{u}/2 \\
 \cos\left(\frac{3\pi}{2N}\right) = \int_{\Delta u - \Delta \bar{u}/2} R(u) \cos\left(\frac{2\pi \cdot \Delta x \cdot u}{\lambda f}\right) du \\
 \quad \Delta u - \Delta \bar{u}/2 \\
 \dots
 \end{array} \right. \quad (19)$$

Equation set (19) defines a Fourier coefficients *solution* to the problem of describing  $R(u)$  by cosine series, i.e.,

$$5 \quad R(u)|_k = \sum_{n=0}^{N-1=7} \cos\left(\frac{\pi k(2n+1)}{2N}\right) \cdot \cos\left(\frac{2\pi \cdot u \cdot n \cdot \Delta x}{\lambda f}\right) \quad (20)$$

This solution preferably defines a matching between individual pixels in the SLM ( $u$ ) and the CCD ( $k$ ).  $u \in [k \cdot \Delta u - \Delta \bar{u}/2, k \cdot \Delta u + \Delta \bar{u}/2]$ .

10 It should be noted that equation 20 actually defines a family of solutions, thus, in some embodiments of the invention, standard geometries of SLMs and CCDs are used, while in others one or both of the SLM and CCD are modified to better fit a particular matching solution. In the general case, the matching may be performed by using neutral filters and by matching at least the locations, if not the sizes of CCD and SLM pixels.

In a preferred embodiment of the invention,, the above matching condition(s) are applied towards other discrete linear transforms which are to be applied using Fourier lens:

$$15 \quad F(k) = \sum_{n=0}^{N-1} f(n) \cdot C(k, n) \quad (21)$$

Applying the same procedure, as in equations (12)-(20), (18) now reads:

$$C(k,n) = \int_{k \cdot \Delta u - \Delta \bar{u} / 2}^{k \cdot \Delta u + \Delta \bar{u} / 2} R(u) \cdot \cos\left(\frac{2\pi \cdot n \cdot \Delta x}{\lambda f}\right) \cdot du, \quad n, k = 0, 1, \dots, N-1 \quad (22)$$

So for the general 1D linear transform:

$$R(u)|_k = \sum_{n=0}^{N-1} C(k,n) \cdot \cos\left(\frac{2\pi \cdot u \cdot n \cdot \Delta x}{\lambda f}\right), \quad u|_k \in [k\Delta u - \Delta \bar{u} / 2, k\Delta u + \Delta \bar{u} / 2] \quad (23)$$

or the matching condition of equation (11) can be used. In the context of matching conditions it should be noted that a matrix of sub-elements is not required. Rather, it is sufficient that there be a correspondence between the pixels in the SLM and the pixels in the CCD. A simple construction is that of a matrix of elements.

In an alternative preferred embodiment of the invention, DCT, FFT or block transforms are achieved using a holographic lens, for example replacing lens-matrix 94, individual lens-elements 95 and/or other optical elements (described below). Alternatively or additionally, two dimensional holograms may be used, for example, by providing arrays of phase and amplitude modifying materials, instead of refracting elements. Alternatively or additionally, a look-up table based approach to transforming may be used, for example using the look-up table methods described in US Patent No. 4,892,370, the disclosure of which is incorporated herein by reference. Alternatively or additionally, acousto-optical type optical elements are used. An advantage of transform-lens, such as described with reference to Figs. 4A-4D, is that they are better matched to the physical model of the compression, i.e., transforming data from an image space into a transform space. Holograms are a general purpose optical element design method, which although they are very flexible, may have an efficiency penalty. Look-up tables are general purpose solutions which may require a larger and/or more complex optical architecture than a matched architecture such as a lenslet array.

Fig. 5 is a schematic block diagram of an optical JPEG compression system 110, in accordance with another preferred embodiment of the invention, in which the DCT transformed data is further processed prior to being converted to electrical signals. A main difference from the embodiment of Fig. 2 is the provision of an A/D converter 112, which converts the data from an analog representation to a digital representation. Thus, coding (e.g., VLC and Huffman) can be performed optically using various types of available hardware architectures. The Zig-Zag step (26) may be performed before or after quantization, for example, even after the data is converted to electrical signals, by optical sensor 58. An exemplary optical A/D converter is described in "Real-Time Parallel Optical Analog-to-Digital



Conversion", by A. Armand, A.A. Sawchuk, T.C. Strand, D. Bosni and B.H. Soffer, in Optics Letters, Vol. 5 No. 3, March 1980, the disclosure of which is incorporated herein by reference.

In the embodiment of Fig. 5, quantization is shown as being performed on the optical data, for example utilizing an SLM or a controllable attenuator such as an LCA with one or more face polarizers which selectively "divide" DCT coefficients by a weight. Alternatively, the data is quantized after the A/D conversion, for example using a suitable lookup table or a holographic lens. In embodiments where digital data is represented by spatial bit patterns, as in the above paper ("real-time"), quantizing may be performed by spatially blocking out certain bits. In embodiments where digital data is represented temporally, temporal filtering may be used in which certain pixels are darkened, in synchrony to the bit order of the light pattern, so that those bits are blocked out. It is noted that the quantization step and the encoding step (at least the VLC) may be combined as a single step, using relatively standard tables, as known in the art of electronic JPEG.

In some embodiments of the invention, it is desirable to achieve different spatial and/or bit resolutions for different parts of the image. In one example, the CCD can be read out at varying resolutions, responsive to the desired spatial resolution. In another example the light source is defocused for portions where a lower resolution is required. Alternatively or additionally, the quantization is varied between the blocks. If for example quantization is achieved by selective blocking of pixels, this blocking may be implemented using an electrically controllable spatial filter, for example an LCD, which can be set to the desired quantization.

In a preferred embodiment of the invention it is desirable to simultaneously generate multiple resolutions of JPEG data. In a preferred embodiment of the invention, this is achieved by parallel application of the JPEG algorithm, using hardware as described herein. Alternatively, this may be achieved (for example in the embodiment of Fig. 2) by reading out the CCD at different resolutions, for different JPEG resolution levels. Alternatively, varying resolutions may be achieved by zooming the source image 92 up or down, for example using a zooming lens or by suitable control of an SLM which generates the light.

Compression of color images may be achieved by converting the image from an RGB format into a YUV format (if it is not already so represented) and then compressing each of the Y, U and V components. Typically, only the Y component is compressed at a full spatial resolution, while the U and V components are compressed at half their spatial resolution. In one preferred embodiment of the invention, different hardware is provided for the different

components. Alternatively, the same hardware is used, sequentially. Alternatively, other color component separation methods may be used.

In a preferred embodiment of the invention, an image sequence, such as a video sequence is compressed utilizing the above methodology. In a preferred embodiment of the invention, each of the images in the sequence sequences is compressed in turn using the above method of JPEG compression, providing a series of JPEG compressed images. In a preferred embodiment of the invention, inter-frame compression is achieved by motion estimation for example using adaptive differential coding by subtracting consecutive images. In a preferred embodiment of the invention, consecutive images are subtracted using an SLM which is driven with a previous image's density distribution. In a self-electro-optic effect device, the SLM can be programmed directly using the previous image, without requiring external electronics to store or otherwise manipulate the image.

Fig. 6 is a simplified schematic flowchart of a base-line method 120 of MPEG-compliant compression, which flowchart does not show various feedback loops often utilized in the MPEG compression method. One of the main advantages of the MPEG compression method over the JPEG compression method is that the MPEG method takes into account similarities between consecutive images. One of the main tools for similarity determination is motion estimation, in which the motion of portions of the image are determined, so that an image can be reconstructed from spatially translated parts of previous images. Transmitting only the amount of translation usually requires less bandwidth than transmitting coefficients for an entire block. Thus, in an exemplary method, input data is transformed using a DCT transform (122). Motion estimation is performed (124). The resulting coefficients of translation data is quantized (126), encoded (128) and combined with a header (130) to form a data stream.

In a preferred embodiment of the invention, alternatively or additionally to performing the DCT step using optical processing methods, also the motion estimation is performed using optical processing. In a preferred embodiment of the invention, motion estimation is performed by performing an autocorrelation of the source data with itself, allowing small amounts of block motion, using well known optical means, to determine block motion. Alternatively however, a DCT based motion estimation scheme is used. Thus, a same or similar hardware as used for the DCT may also be used for at least part of the motion estimation. A method of motion estimation using DCT is described in a Ph.D. Dissertation titled "Low Complexity and High Throughput Fully DCT-Based Motion Compensated Video Coders", by Ut-Va Koc, presented in 1996 to K.J. Ray Liu of the institute for systems research

and sponsored by the National Science Foundation Engineering Research Center Program, the University of Maryland, Harvard University and Industry, in U.V. Koc and K.J.R. Liu, "Low-Complexity Motion Estimation Techniques", U.S. Patent No. 5,790,686, issued August 4, 1998 and in U.V. Koc and K.J.R. Liu, "DCT-Based Motion Estimation", IEEE Trans. on Image Processing, Vol. 7, No. 7, pp. 948-965, July, 1998, the disclosures of which are incorporated herein by reference. The method described therein can be summarized as follows (based on table 4.2 in the Ph.D. dissertation), with the DCT portions preferably being performed as described herein. Preferably, other elements of the process are also implemented using optical components, for example peak finding.

- 10 a. Compute the 2D DCT coefficients of second kind (2D-DCT-II) of an  $N \times N$  block of pixels at the current frame  $t$ ,  $\{x_t(m,n); m,n \in \{0, \dots, N-1\}\}$ .
- b. Convert stored 2D-DCT-II coefficients of the corresponding  $N \times N$  block of pixels at the previous frame  $t-1$ ,  $\{x_{t-1}(m,n); m,n \in \{0, \dots, N-1\}\}$  into 2D DCT coefficients of first kind (2D-DCT-I) through a simple rotation unit  $T$ .
- 15 c. Find the pseudo phases  $\{g^{CS}(k,l); k=0,1,\dots,N-1; l=1,2,\dots,N\}$  and  $\{g^{SC}(k,l); k=1,2,\dots,N; l=0,1,\dots,N-1\}$ , which are calculated from the DCT coefficients independently at each spectral location.
- d. Determine the normalized pseudo phases  $f(k,l)$  and  $g(k,l)$  from  $g^{CS}$  and  $g^{SC}$  by setting ill-formed pseudo phases to zero.
- 20 e. obtain the inverse DCT (2D-IDCT-II) of  $f(k,l)$  and  $g(k,l)$  as  $DCS(m,n)$  and  $DSC(m,n)$  for  $m,n \in \{0, \dots, N-1\}$  respectively.
- f. Find peaks in  $DSC$  and  $DCS$ , which peak positions represent the shift amounts and peak signs represent the direction of movement.
- g. Estimate the displacement from the signs and positions of the found peaks.

25 It is noted that even in this method of motion estimation, some processing is required beyond the DCT, however, a significant portion of the computation may be dealt with by DCT or IDCT transforming of the data (in parallel or in sequence for each block). In a preferred embodiment of the invention, the previous image and/or its DCT coefficients are stored and/or provided using suitable electronics. Possibly, the optical DCT transforming elements are used for performing DCT and IDCT. Alternatively to the above method of motion estimation, direct correlation of image blocks may be used to estimate motion, for example, using image correlation optical systems known in the art as part of the compression process.

The above description has centered on compression, however, it should be noted, that decompression is very similar to compression and can often utilize similar or the same

hardware. In the example of JPEG, DCT (for compression) and inverse DCT (for decompression) can be performed using a same optical transform element. In the example of MPEG, motion compensation, i.e., recreating images by compensating for the effect of motion, which motion was determined using motion estimation, can utilize a similar DCT-based method, also described in the above doctorate. It is noted that for some decompression methods, there is a requirement for some processing before the transforming of coefficients into an image domain. For example, in JPEG de-compression, the compressed image data is un-runlength encoded and de-quantized prior to being IDCTed. As with compression, these processing steps may be performed optically and/or electronically, depending on the implementation.

Fig. 7A is a schematic diagram of a direct-compression camera system 200, in accordance with a preferred embodiment of the invention. In system 200, an image of a real object 202 is acquired directly as transformed and/or compressed data, rather than being acquired as image data which is later compressed. There are many applications in which an image is acquired in order to be stored on a digital media or in order to be transmitted over bandwidth-limited transmission lines. Examples of such applications include digital cameras, security cameras, teleconferencing systems, live-feed TV cameras and video-telephones. In a preferred embodiment of the invention, the data is acquired in a compressed manner, using the above described methods of compressing optical data, except that it is preferably the original optical waves, arriving from the object, that are compressed, rather than an electronic representation which is separately acquired and compressed.

In the exemplary system of Fig. 7A, an optional object lens 204 focuses and directs the light from object 202 onto a DCT lens (or lens matrix) 206. Lens 206 may also comprise other optical elements which perform further steps of the image compression method. The processed light is collected by a CCD 208 and then further processed and stored in a storage 210. In real-time embodiments, the acquired data may be transmitted, instead of or in addition to storage. The compression method performed may be a method suitable for still images, such as JPEG or a method suitable for moving images.

In a preferred embodiment of the invention, DCT lens 206 is designed to operate on white light. Alternatively, the light arriving from the scene is filtered so that it is monochrome. Alternatively or additionally, the image is acquired under controlled lighting situations, so that the light has known characteristics, such as being coherent, monochromatic or formed of a small number of narrow spectral bands. Alternatively or additionally, the image is acquired using a monochromatic light, possible a laser flash, so that the characteristics of the light are

controlled by system 200. Such controlled lighting is especially useful for low-light level cameras, such as those using GICCD (Gated Intensified CCD) technology. Also, the use of coherent light simplifies the use of hologram-based image processing techniques.

Alternatively or additionally to an objective lens 204, a light encoding module, such as a combination CCD/SLM may be used, to convert incoming light into light having desired spatial and spectral characteristics. Alternatively or additionally, a self-electro-optical effect shutter is used, in which the impinging light is used to modulate the transmission of last or other controlled light.

Fig. 7B is a schematic block diagram of a YUV-separated implementation 220 of the embodiment of Fig. 7A. Color images may be compressed by separately compressing each color component, or more commonly, each of the YUV components. These components may be determined using a look-up table or by simple arithmetic on the R, G and B components of an incoming image. These separations may be performed using optical means and/or electronic means, shown generally as a splitter 222. Each of the resulting color components (224) is then processed separately, using a dedicated DCT 206 and a dedicated CCD 208. The results are then added using a combiner 226. It should be noted that the U component and the V component are usually processed at a lower resolution than the Y component. Thus, the U and the V can share optical components. Alternatively or additionally, all three components are processed using a single optical path, for example on different parts of a same lens-CCD set. Alternatively or additionally, the three components are processed sequentially.

A component which performs image compression or decompression may be packed in various ways, depending on the application. In one application, a PC graphics card includes an optical processor for aiding in displaying MPEG images. In another example, a CCD camera includes an MPEG or a JPEG optical module so that they can provide a compressed data output as well as a standard data output.

In a preferred embodiment of the invention, the above described optical elements are provided embedded in a transparent substrate, such as a clear plastic or glass, so that once the elements are coupled, there is no relative movement due to vibration, heat or other external forces. It should be noted that pixel-sized transverse shifts in the optical elements do not substantially affect the output, providing the SLM can be controlled to shift its image by the pixel shift error. In a preferred embodiment of the invention, the optical elements are manufactured and tested without a surrounding matrix or with a liquid surrounding matrix, which is then solidified when the relative positions of the optical elements are determined. In a preferred embodiment of the invention, the optical processor is calibrated by entering known

data and measuring the compressed output.

Fig. 8 is a schematic diagram of a lithographic implementation of an optical compression system 300 in accordance with a preferred embodiment of the invention. An advantage of lithographic optics is that they can be fabricated in large batches, and, depending on the process, in conjunction with the forming of electronic circuits on a same substrate. It should be noted that most lithographic implementations utilize reflective optics rather than transmissive optics. The above description has focused on transmissive optics, however, reflective optics can also be used for non-lithographic optical processors. Various lithographic implementations will occur to a person skilled in the art, however, an exemplary embodiment is shown in Fig. 8.

System 300 comprises generally of a substrate 301, one or more reflective surfaces 303 which are etched and/or otherwise lithographically processed or micro-machined to form reflective optical elements and an interposing clear medium 305. An SLM or a diode array 302 is used to provide an image. The light is reflected off substrate 301 to a reflective DCT lens 304. The transformed light is reflected back to substrate 301 and then to a CCD or other optical array detector 306. Optionally, the CCD array or other optical, electrical or electro-optical elements may be formed directly on the substrate, for example as indicated by reference 308. In one example, a quantizer, or a holographic reflecting lens are formed at location 308. Possibly, reference 308 indicates an active element, such as an LCD array.

In a preferred embodiment of the invention, device 300 is manufactured to DCT a single 8x8 block rather than a whole image. A plurality of systems 300 is preferably used to compress an entire image. Alternatively, system 300 is manufactured to process a single vector rather than an array. Although system 300 may form a part of a dedicated JPEG or MPEG decoder or encoder, in a preferred embodiment of the invention, one or more system 300 type elements are used for the construction of digital signal processor or other integrated circuits, for example to assist in high-end graphical applications.

The above description has centered on DCT based compression methods. However, other transform based compression methods may also be implemented in accordance with preferred embodiments of the invention. In one example, a wavelet compression method is implemented using a block DWT (discrete wavelet transform). Possibly, there is an overlap between blocks. Such a transform is described, for example in G. Strang and T. Nguyen, "Wavelets and Filter Banks", Wellesly-Cambridge Press, 1997, pp. 502, the disclosure of which is incorporated herein by reference. Preferably, such a wavelet compression implementation includes bit-plane coding techniques such as SPIHT or EZW, possibly

implemented using a lookup table.

The above description has centered on image compression, however, in accordance with a preferred embodiment of the invention, optical components are used for compressing other types of signals, for example, audio signals. It is noted, however, that image compression is generally more suitable for transform based compression and being two-dimensional, is more computationally-complex to compress than other types of data.

In the above detailed description, various types of optical data representations are suggested, as well as various types of optical systems. In a preferred embodiment of the invention, the optical representation used is selected to match the optical system, for example, an analog representation for an analog system. In some cases, the data may be converted between representations, to take advantage of particular optical configurations, for example digital optical data may be converted into analog optical data to use a particular lenslet-based implementation of a DCT transforming element.

The optical processing hardware is preferably dedicated for particular tasks. Alternatively, in some preferred embodiments of the invention, the same hardware components may be used for different steps in a process (such as a DCT component for compression and for motion estimation), for different processes (such as compression and decompression) and/or for different data blocks in a same process, such as in serial processing of data blocks). Alternatively or additionally, the hardware may be programmable, at least to some extent. For example, by modifying the behavior of an SLM and a CCD which form part of a Fourier-based data transform optical component, different type of transforms can be achieved with a single hardware, for example, DCT and DST. Alternatively or additionally, the matching layer may be programmable, for example being an addressable LCD, so that the size and/or location of pinholes can be controlled. Alternatively or additionally, by controlling the opacity of single LCD cells different continuous spatial filtering configurations can be achieved.

It will be appreciated that the above described methods of optical processing may be varied in many ways, including, changing the order of steps, which steps are performed using electrical components and which steps are performed using optical components, the representation of the data and/or the hardware design. In addition, various distributed and/or centralized hardware configurations may be used to implement the above invention. In addition, a multiplicity of various features, both of methods and of devices, have been described. It should be appreciated that different features may be combined in different ways. In particular, not all the features shown above in a particular embodiment are necessary in

every similar preferred embodiment of the invention. Further, combinations of the above features are also considered to be within the scope of some preferred embodiments of the invention. In addition, the scope of the invention includes methods of using, constructing, calibrating and/or maintaining the apparatus described herein. When used in the following  
5 claims, the terms "comprises", "comprising", "includes", "including" or the like mean "including but not limited to".



## CLAIMS

1. A method of image compression, comprising:  
5 providing image-data encoding light;  
transforming said light from an image space to a transform space utilizing an optical component; and  
converting said transformed light into electrical signals, which electrical signals represent a compressed representation of said image data.
- 10 2. A method according to claim 1, wherein said converting comprises converting after quantization.
3. A method of image de-compression, comprising:  
15 providing compressed-image-data encoding light;  
transforming said light from a transform space to an image space utilizing an optical component; and  
converting said transformed light into electrical signals, which electrical signals represent said image data.
- 20 4. A method according to any of claims 1-3, wherein said transforming comprises transforming using one or more optical elements which perform a block transform.
5. A method according to claim 4, wherein said one or more optical elements comprises a  
25 matrix of optical lens elements.
6. A method according to claim 5, wherein at least one of said optical lens elements comprises a lenslet array which performs a block transform for a single block.
- 30 7. A method according to claim 4, wherein said one or more optical elements comprises an element which performs a vector by matrix multiplication.
8. A method according to claim 4, wherein said one or more optical elements comprises an element which generates a matrix product.

9. A method according to claim 8, wherein said matrix product comprises a triple matrix product.

5 10. A method according to claim 4, wherein said transforming utilizes at least one electrical component for transferring data between said at least one optical component.

11. A method according to any of claims 1-10, wherein said image is compressed using a JPEG standard.

10

12. A method according to any of claims 1-10, wherein said image is compressed using an MPEG standard.

15

13. A method according to any of claims 1-10, wherein said image is compressed using a wavelet compression method.

14. A method according to any of claims 1-13, wherein said image data represents an image sequence.

20

15. Apparatus for direct acquisition of compressed image data, comprising:  
at least one optical element which receives light waves from an imaged object and which transforms said image into a transform space; and  
an optical detector which receives said transformed light and generates electronic signals responsive to said received light.

25

16. Apparatus according to claim 15, comprising an optical quantizer which quantizes said transformed light prior to its reception by said detector.

30

17. Apparatus according to claim 15, comprising an electronic quantizer which quantizes said electronic signals to produce compressed data.

18. Apparatus according to claim 15, wherein said optical detector quantizes said light.

19. Apparatus according to any of claims 15-18, wherein said at least one optical element

comprises a single optical element which performs said transforming

20. Apparatus according to any of claims 15-19, comprising a storage unit for storing at least one set of said electronic signals, corresponding to a still image.

21. Apparatus according to any of claims 15-19, comprising a storage unit for storing at least one set of said electronic signals, corresponding to an image sequence.

22. Apparatus according to any of claims 15-21, wherein said transform space comprises a DCT transform space.

23. Apparatus according to any of claims 15-21, wherein said transform space comprises a wavelet transform space.

24. A block-transform optical element, comprising:  
a plurality of optical groups each group comprising at least one optical sub-element, wherein each of said optical groups transforms a block of data.

25. An element according to claim 24, wherein said at least one sub-element comprises a lenslet array portion.

26. An element according to claim 24 or claim 25, wherein said plurality of optical groups are arranged as a matrix.

27. An element according to any of claims 24-26, wherein said element performs a JPEG-DCT transform.

28. An element according to any of claims 24-26, wherein said element performs an inverse DCT transform.

29. An element according to any of claims 24-26, wherein said element performs a wavelet transform.

30. An element according to any of claims 24-29, wherein said optical element performs

said transform on data arranged as a spatially impulse image.

31. An element according to any of claims 24-27, wherein said optical element performs said transform on data arranged as a continuous image.

5

32. An element according to any of claims 24-31, wherein said transform comprises a linear transform.

10

33. An element according to any of claims 24-32, wherein said transform comprises a non-separable transform.

34. An element according to any of claims 24-33, wherein said optical groups overlap.

15

35. An element according to any of claims 24-33, wherein said optical groups do not overlap.

20

36. A method of DCT-like transforming of data, comprising:  
providing optical waves which encode said data; and  
passing said waves through at least one optical element, which optical element modifies said optical waves into second optical waves carrying a transform of said data.

37. A method according to claim 36, wherein said transform comprises a block transform.

25

38. A method according to any of claims 36 or 37, wherein said at least one optical element is an atomic optical element.

39. A method according to any of claims 36 or 37, wherein said at least one optical element comprises a plurality of optical elements.

30

40. A method according to any of claims 36-39, wherein said at least one optical element comprises a discrete optical processing element.

41. A method according to any of claims 36-39, wherein said at least one optical element comprises substantially only continuous optical processing element.

42. A method according to any of claims 36-41, wherein said transform is a JPEG-DCT transform.

5 43. A method according to any of claims 36-41, wherein said transform is an inverse DCT transform.

44. A method of optical motion estimation, comprising:  
providing a first set of light waves encoding data of a first image block;  
10 DCT transforming said first set of light waves using an optical component;  
providing a second set of light waves encoding data of a second image block;  
DCT transforming said second set of light waves using an optical component; and  
processing said first and said second DCT transformed data sets to determine an  
amount of relative motion of said two blocks.

15 45. A method according to claim 44, wherein both of said DCT transforms utilize a same optical component for said transforming.

46. A method according to claim 44 or claim 45, wherein said processing comprises  
20 electronically processing said transformed data sets.

47. A method according to any of claims 44-46, comprising utilizing said determined motion for generating a compressed image stream.

25 48. A method of transforming data using a discrete transform, comprising:  
preprocessing said data to yield optically encoded data;  
Fourier transforming said data using a Fourier lens; and  
postprocessing said data to yield transformed data.

30 49. A method according to claim 48, wherein said preprocessing comprises optically preprocessing.

50. A method according to claim 49, wherein said preprocessing comprises matching said data to said postprocessing.

51. A method according to claim 50, wherein said postprocessing comprises acquiring said data and wherein said matching comprises matching to said acquisition.

5 52. A method according to claim 51, wherein said postprocessing comprises spatially modulating said light.

53. A method according to claim 48, wherein said preprocessing comprises spatially modulating said light.

10 54. A method according to claim 52 or claim 53, wherein said spatially modulating comprises masking said data using an array of pinholes.

15 55. A method according to claim 52 or claim 53, wherein said spatially modulating comprises continuously varying said amplitude of said data.

56. A method according to any of claims 48-55, wherein said preprocessing comprises mirroring said data.

20 57. A method according to any of claims 48-56, wherein said transform comprises a JPEG-DCT transform.

58. A method according to any of claims 48-56, wherein said transform comprises a wavelet transform.

25 59. A method according to any of claims 48-56, wherein said transform comprises an inverse DCT transform.

30 60. Apparatus for compressed image data manipulation, comprising:  
an input for receiving data;  
at least one optical component for transforming said data between an image space and a transform space; and  
an output for outputting said manipulated data.

61. Apparatus according to claim 60, wherein said received data comprises uncompressed image data and comprising a processor for processing said data after said transform to yield compressed image data to be outputted.

5 62. Apparatus according to claim 60, wherein said received data comprises compressed image data and comprising a processor for processing said data before said transform to yield transform data to be transformed by said optical component for said output.

63. Apparatus according to claim 62, wherein said processor includes an optical D/A  
10 converter.

64. Apparatus according to claim 62, wherein said processor comprises an optical multiplier for de-quantizing data.

15 65. Apparatus according to claim 61 or claim 62, wherein said processor performs at least some of its processing on optic waves.

66. Apparatus according to any of claims 61-65, wherein said processor performs at least some of its processing on electronic signals.

20 67. Apparatus according to any of claims 60-66, comprising an optical motion estimator.

68. Apparatus according to claim 67, wherein said optical motion estimator utilizes said optical component for optical motion estimation.

25 69. Apparatus according to claim 67 or claim 68, wherein said optical motion estimator includes at least one electronic component.

70. Apparatus according to any of claims 60-68, comprising an optical motion  
30 compensator.

71. Apparatus according to claim 70, wherein said optical motion compensator utilizes said optical component for optical motion compensation.

72. Apparatus according to claim 70 or claim 71, wherein said optical motion compensator includes at least one electronic component.

73. Apparatus according to any of claims 60-72, wherein said data is compressed using a JPEG compression.

74. Apparatus according to any of claims 60-72, wherein said data is compressed using a wavelet compression.

75. Apparatus according to any of claims 60-72, wherein said data is compressed using an MPEG compression.

76. Apparatus according to any of claims 60-75, wherein said data comprises an image sequence.

77. Apparatus according to any of claims 60-74, wherein said data comprises is a single image.

78. Apparatus according top any of claims 60-77, wherein said data is manipulated as blocks.

79. Apparatus according to claims 78, wherein at least two of said blocks are manipulated in parallel.

80. Apparatus according to claims 78, wherein at least two of said blocks are manipulated in series and comprising a buffer circuit for directing said blocks in series into a single optical component.

81. Apparatus according to any of claims 60-80, wherein said optical component comprises a discrete data transforming optical element.

82. Apparatus according to any of claims 60-81, wherein said optical component comprises a holographic lens.



83. Apparatus according to any of claims 60-82, wherein said optical component comprises an acousto-optic element.

84. Apparatus according to any of claims 60-83, wherein said optical component  
5 comprises an optical analog to digital converter.

85. Apparatus according to any of claims 60-84, wherein said optical component comprises an optical digital to analog converter.

10 86. Apparatus according to any of claims 60-85, wherein said optical component comprises matrix product calculating element.

15

20

For the applicant,



Fenster & Co. Patent attorneys Ltd.  
c:141/00863

25

1/9




FIG.1

2/9




FIG.2

50

3/9




FIG. 3A




FIG. 3B

4/9




FIG. 4A




FIG. 4B




FIG. 4C

5/9




FIG. 4D

6/9




FIG.5

110

7/9




FIG. 6



8/9




FIG. 7A




FIG. 7B




FIG. 8